

CTI Route Point Configuration

[Add a New CTI Route Point](#)
[Back to Find/List CTI Route Points](#)

Directory Numbers

- 7718 Line 1 - 103 in
- 7719 EXTS_PE_PT
- 7718 Line 2 - Add DN
- 7719

Device: **AA_RP_3 (AA_RP_3 (Naga) - 103)**
 Registration: **Unknown**
 IP Address:

Status: Ready

CTI Route Point Configuration

Device Information

Device Name*

Description

Device Pool* [\(View details\)](#)

Calling Search Space

Location

* indicates a required item.

Directory Number: 103 (EXTS_PE_PT)

Status: Ready

Directory Number

Directory Number*

Partition

Directory Number Settings

Voice Mail Profile
 (Choose <None> to use default)

Calling Search Space

User Hold Audio Source

Network Hold Audio Source

Call Waiting

Auto Answer

Call Forward and Pickup Settings

	Voice Mail	Destination	Calling Search Space
Forward All	<input type="checkbox"/>	<input type="text" value="90126533238"/>	<input type="text" value="CSS_ALL"/>

Status: Ready

Pattern Definition

Translation Pattern

Partition

Numbering Plan*

Route Filter

Calling Search Space

Route Option Route this pattern Block this pattern

Provide Outside Dial Tone Urgent Priority

Calling Party Transformations

Use Calling Party's External Phone Number Mask

Calling Party Transform Mask

Prefix Digits (Outgoing Calls)

Called Party Transformations

Discard Digits

Called Party Transform Mask

Prefix Digits (Outgoing Calls)